



70V Mixer Amplifier with Media Player

MIXAMP-60

SKU: 39443 UPC: 612935000000

The MixAmp-60 Mixer Amplifier with MP3, FM tuner & Bluetooth, is ideal for schools, supermarkets, convenience stores, banks, retail stores and similar environments. It is an all-in-one solution with built-in audio sources, pre-amp mixing, audio amplification, expandability to external sources, microphones, etc., in one small, rack-mountable chassis.

The MixAmp-60 integrates combinations of up to 3 microphones and 4 external audio sources in addition to its built-in FM Tuner, Bluetooth receiver, USB, and SD card MP3 player.

Convenient front panel controls allow for precise volume level of all connected sources as well as an integrated LCD display showing currently selected audio from the built-in sources. Background Music (BGM) and Music On Hold (MOH) integration are available as well as a Telephone Paging Input. Phantom Power is available for the primary microphone as well as adjustable ducking levels.

The Russound MIXAMP-60 features a diverse array of input options, and enough power to drive a versatile commercial sound system for a small- to medium-sized venue. Its 60 watts of amplification can be used to drive speakers in a variety of configurations, with 4-ohm, 8-ohm, 16-ohm, 70-volt, or 100-volt compatibility. There's also a built-in FM tuner and an integrated MP3 player on the front panel with a USB Type-A input and SD card slot for physical media.

A wealth of connections makes the MIXAMP-60 a great centerpiece for an all-in-one system for a small business. There's a balanced XLR input with phantom power that's ideal for a paging microphone. There are two Phoenix-style connectors with mic/line compatibility and dual stereo RCA inputs for additional sources. The sixth input is a dedicated telephone input/output that supports paging and music on hold.

Features

- Compact Design
- Built-in 70V/100V transformer technology
- Tabletop amplifier with MP3 player, FM radio & Bluetooth. Antenna included in the box
- 60W Power Output
- Speaker outputs of 70V, 100V, 4 Ohms, 8 Ohms, and 16 Ohms
- MP3 player with USB/SD input on front panel, IR remote control included for MP3 player, FM radio and Bluetooth
- LED indicators for power, clipping, protection and signal
- Mic 1 is a balanced XLR input with configurable phantom power support. Mics 2 & 3 are switchable, unbalanced, removable screw-down Phoenix connectors types and can alternate between microphones or line inputs.
- Includes a built-in telephone input with VOX priority and MOH (Music on Hold) output.
- Convenient Front-Panel Volume Controls for all physical inputs, MP3/FM, master volume as well as bass/treble
- Line out for use with an optional external amplifier if more power is needed
- Built-in short-circuit, clipping, overload and overtemperature protection
- Rack-mountable with included rack mount ears

Specifications: Shipping Dimensions: 24"W x 17"D x 8"H (60.96 x 43.18 x 20.32cm) single unit Shipping Weight: 18 lbs (8.16 kg) Rated Power Output: 60W Speaker Outputs: 70V/100V/4?/8?/16?, RCA Line Out Connectors: Mic1 -



Balanced XLR with phantom power Frequency Response: 60Hz-15kHz(+/-3dB) S/N Ratio: Line \approx 85dB, Mic \approx 72dB THD: Less than 0.5% Protection: short-circuit, clip, overload and high temp protection Power Consumption: 100W Power Supply: 110-230VAC, 50-60Hz Dimensions: 12.6" x 8.27" x 3.54" (320 x 210 x 90 mm) Weight: 9.5 lbs (4.3kg) What's in the box: Russound MIXAMP-60 owner's manual 70/100V Mixer/amplifier Two 3-pin Euroblock connectors (installed) IR Remote control (installed CR2025 battery) 5' AC Power cord (IEC 3-pin) 5' FM Wire antenna w/threaded coaxial connector 2 Rack ears Nine 5mm counter-sunk screws Owner's manual