



PANAMAX

Replacement Battery Pack for MX5102

BC-MX5102

SKU: 12716 UPC: 5061600862

Power line conditioner with voltage regulator surge protector & battery backup.

1800 Joule protection. 2 Outlets include 600va/360w battery backup to maintain power to components during blackouts and brownouts. Automatic voltage regulation circuitry for consistent power. Lift (linear filtration technology) filters noise evenly across the entire frequency band. Resettable circuit breakers. Front-panel lcd shows line voltage as well as time remaining during battery backup. Learning ir control for orderly shutdown of components. Dual ir outputs (requires infrared flashers/ not included). 3 Pairs of rf coaxial jack connections for cable/ satellite/ and antenna tv signals. 1 Ethernet input and output. 1 Phone line input and output. 12-Volt trigger input. Removable panel for battery access and replacement. Includes hardware for rack mounting. 10 Surge-protected outlets in four isolated banks:

- 4 switched
- 2 battery backup
- 2 switched high-current
- 2 always on