



470145

SKU: 30620 UPC: 811815029489

Wilson Pro 470145 weBoost Home Complete Signal Booster Kit is the improved version of the weBoost Connect 4G-X. It has a completely redesigned aesthetic, so it looks great in your home, and uses RG11 cables with standard F connectors, so it's easier to install. The uplink and downlink powers have been increased, so you get better performance even further from the cell towers, so it's perfect for very rural areas, and the booster will provide even more coverage if you happen to have a strong outside signal.

Features:

- Boosts the Voice, 3G, and 4G LTE networks from all major carriers
- Most powerful 4G system available
- Can cover up to 7,500 sq ft with a strong existing outside signal. A weaker outside signal will result in less coverage.
- DIY Installation

Specifications:

- Frequency:
 - Band 12/17: 700 Mhz; BAND 13 - 700 Mhz;
 - Band 5: 850 Mhz; BAND 4 - 1700/2100 Mhz;
 - Band 25/2: 1900 Mhz
- Max Gain: 72 decibels (dB)
- Impedance: 75 Ohms
- Power: 110-240V AC, 50-60 Hz, 20 W
- Connectors: F-Female
- Dimensions: 8.25 x 6 x 2.4 in
- Weight: 1.55 lbs (amplifier only)
- Supported Carriers:
 - AT&T 2G/3G/4G HSPA+ plus 4G LTE
 - Verizon 2G/3G plus 4G LTE
 - Sprint 2G/3G plus 4G LTE
 - US Cellular 2G/3G plus 4G LTE
 - Alltel 2G/3G
 - T-Mobile 2G plus 3G, 4G HSPA+ & 4G LTE
 - All other carriers using 800 MHz, 1900 MHz, and AWS 1700/2100 MHz