

DENON



9.4 Channel 105W 8K AV Receiver with HEOS

AVR-X3800H

SKU: 139509 UPC: 747192138417

Denon AVR-X3800H 9.4 Channel Network AV Receiver. With nine channels of amplification, up to four independent subwoofers, Dolby Atmos and DTS:X, plus IMAX Enhanced and Auro 3D, the AVR-X3800H envelops larger living spaces in theater-quality sound. Enjoy amazing 8K video quality and with HEOS® Built-in, wirelessly stream and share online music between rooms. Discrete high-current amplifiers deliver up to 105W per channel (at 8 ohms, 20- 20kHz, THD 0.08%)—enough power to drive any speaker. Get enveloped in sound with Dolby Atmos®, DTS:X®, IMAX Enhanced and Auro 3D, along with Dolby Surround, DTS Neural:X and Auro-Matic upmixer to optimize legacy content. AVR-X3800H offers many setup options and flexibility to adjust your home theater to meet your needs. Supports 11.4 channel processing capability, Pre- Amplifier mode, and optional Dirac Live upgradability (with fee, coming soon in 2023). 8K video is supported on all six HDMI inputs and two of the three outputs. Enjoy easy video compatibility and great picture quality with HLG, HDR, Dolby Vision, HDR10+, and Dynamic HDR passthrough.

- Supports 9.4 or 5.1.4-Channel Audio
- Up to 105W per Channel at 8 Ohms
- Up to 8K HDR Video on All HDMI Inputs
- Use with HEOS for Multi-Room Audio
- Dolby Atmos, DTS:X & IMAX Enhanced
- Pre-Amplifier Mode
- 11.4-Channel Processing
- Wi-Fi & Bluetooth Connectivity
- Audyssey MultEQ Room Calibration
- Next-Gen Gaming Support

Number of Power Amps	9
Power Output	105 watts per channel (8 ohm, 20Hz-20Khz, 0.08% 2ch drive) 135 watts per channel (6 ohm, 1khz, 0.7% 2ch drive) 215 watts per channel (6 ohm, 1khz, 10% 1ch drive)
Multi-Room Zones	2
Zone Audio Source	HDMI; Optical, Coax, Network, USB; Analog
Zone Audio Output	Speaker, Pre-Out
Zone HDMI Output from HDMI Source	Yes
Speaker A / B	Assignable
Bi-amp Drive	Assignable
Multi-Room Speaker Terminal	Assignable
Front Inputs	USB / Headphone
AM/FM Tuner	Yes
HDMI In/Out	6/3
Analog In/Out	5/0
Phono (MM) In	Yes
Digital In: Optical / Coaxial	2 / 2
Multi-Room Out: Analog / Digital	1 / 0
Multichannel Pre-Out	Yes (11.4)

Subwoofer Out	4 (independent)
Number of Speaker Terminals	11
System Remote Control	RC-1253
DC Trigger Output	1
Remote Control IR Input	Yes
Remote Control IR Output	Yes
IP Control	Yes
RS232 Control	Yes
Web Control	Yes
App Control	Yes
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32 Dirac Live (upgrade)
Dimensions (W x D x H) in Inches	Antenna: Horizontal: 17.1 x 15.3 x 6.6 Antenna: Vertical: 17.1 x 15.3 x 9.3 W/O Antenna: 17.1 x 14.9 x 6.6
Weight	27.6 lbs