



## Integrated 4 Source 4 Zone Stereo Audio Power Amplifier

K-1323

SKU: 2291

### Karbon Sound K-1323 Integrated 4 Source / 4 Zone Stereo Audio Power Amplifier

#### Features

- Four-in and Five-out (4 Speaker output, 1 Headphone output)
- Built-In audio digital to analog converter (DAC)
- Audio DAC lock indicator.
- Provides two interfaces of digital audio input (Coaxial & Optical)
- Provides Two interfaces of stereo audio input (RCA&3.5mm phone jack)
- Support dynamic microphone input.
- Independent microphone level control.
- Provides headphone output.
- Provides line loopout expanding.
- Large detachable terminal block (supplied) for quick and easy installation.
- Screw terminals handle wire sizes from 24 to 12 gauge

#### Specifications:

- Speaker Audio Power Amplifier (x4)
- Amplifier Type: Stereo Class-D
- Output power: 15W (rms) per channel (@RL=4 ohm)
- THD+N :0.06% (@RL=8 ohm, f= 1 kHz)
- Minimum load Resistance :4 ohm
- Includes Speaker Protection Circuit.

#### Earphone Audio Power Amplifier

- Output power: 105mW(rms) per channel
- THD+N :0.05 % (@ RL=16 ohm, f= 1kHz)
- Minimum load resistance :16

#### Power & Dimensions:

- Power Consumed: 9A Max
- Power Source: DC 12 Volts
- Size (LxWxH): 285mm x 128mm x43mm
- Net Weight (unit only): 0.8 Kg