



2-Channel RF Receiver

SK-910RB2-4Q

SKU: 27649 UPC: 676544000000

The SK-910RB2-4Q from Seco-Larm is a 2 Channel RF Receiver, 433.92MHz, Two Relays.

Features

- Five programmable relay output modes:
 - 4-Second momentary
 - 1-Second momentary
 - Toggle (ON/OFF)
 - Validity
 - Latch
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (150m)*
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers
- Up to 15 transmitter button codes can be learned

Operating voltage 11~24 VAC/VDC Range Up to 500' (150m) with Seco-Larm transmitter. Range will vary. Output Mode 4-Second momentary, toggle, latch, validity, 1-second momentary Current Draw 8mA@12VDC (standby), 30 mA per channel at 12 VDC (activated) # of Stored Transmitter Codes 15 per channel, 30 per receiver Extended Range Antenna Compatible Yes (SK-91ERSD) Compatible Transmitters Fixed Code: 68 Billion codes, CODEBUMP: 18 Quintillion codes Connectors 8 Quick-connect screw terminals (+, -, with NO/NC/COM for channel 1 and NO/NC/COM for channel 2) Dimensions 3-1/8" x 2-9/16" x 1" (80 x 65 x 25 mm) Receiver Outputs Two Form "C" dry relay contacts (N.O./N.C./COM); 10A@24VDC