



Single Zone 2-Channel WiFi Amplifier

A.1x

SKU: 61600 UPC: 865432000000

The all new VSSL A.1x delivers Hi-Fi audio to a single zone easier than ever! The amplifier can be connected via Wi-Fi or ethernet to stream all of your favorite music through Airplay 2 or Android Casting.

The A.1x was designed to work as a stand-alone amplifier or expand an existing VSSL system. By adding an A.1x to an existing A.6x or A.3x, your system can grow with your needs. Simple, powerful, fun.

Native streaming connects your music to your speakers using the music apps you already know and love. Continue streaming using app like Pandora Radio, Spotify, YouTube, or ANY other music app, and the VSSL A.1x will play it through your favorite speakers.

The VSSL A.1x WiFi amplifier connects through Airplay 2, Chromecast, and Bluetooth.

Features

- Stream audio from your favorite apps to a single zone in your home audio system
- Connects to wired or wireless speakers, and compatible streaming devices
- Built-in Chromecast, Amazon Alexa, Apple Airplay2, Google Cast, Spotify Connect, and Bluetooth compatibility
- Voice controls using Alexa, Google Assistant, and Siri
- Compatible streaming with iOS, Android, Mac, or PC devices
- Can be easily included into existing home automation systems

Zones: 1

EQ: 7-band adjustable

Channels: 2

S/N Ratio: >98dB A-weighted

Amplifier: Class D, 35 W @ 8 Ω , 50 W @ 4 Ω

Freq. Response: 20-20kHz

Inputs: (1) Analog, (1) Optical, (1) Digital Coax, (1) IR, (1) Network

Bluetooth: v4.2, EDR

Wireless Inputs: Airplay2, Chromecast built-in, Spotify Connect, Alexa Cast, Bluetooth

Rack Space: 1U

Outputs: (1) Analog, (1) Optical, (1) Digital Coax, (1) Subwoofer, (1) Network

Dimensions (No Feet): 7.44" W x 1.69" H x 8.69" D



WiFi: 2.4/5.8 GHz Dual Antenna MIMO

Dimensions (with Feet): 7.44" W x 2" H x 8.69" D

Sub Out: RCA, Adjustable cross over 55-200 Hz or by-pass for full range

Weight: 3.5 lbs