



8-Zone 40W Rack Mountable WiFi Streaming Amplifier

Juke 8

SKU: 151298

Power speakers across every room with the Juke multi-room amplifier and control all aspects of the system wirelessly via the easy-to-use app.

Multi-Room Amplification

The Juke-6 powers 6 independent audio zones (12 speaker channels) and the Juke-8 powers 8 zones (16 channels) making it an ideal audio solution for connecting passive in-ceiling and in-wall speakers across an entire house or building.

Need more than 8 zones? Add multiple Jukes to the network and all the zones will appear in the same app allowing you to connect to and stream across all the rooms.

Full Wireless Control

Control all components of your system from the palm of your hand with the Juke Audio application available for Android and Apple.

€

- Play to any combination of zones

- Independent volume slider for every zone

€

- Support streams from multiple users/devices simultaneously

Also accessible on PCs via the web interface.

Specifications
Amplifier Power Output: 40 watts peak per channel (80 watts per zone)
Wireless Inputs: Airplay 2, Spotify Connect, Bluetooth, DLNA
Wired Inputs: 2 USB ports (Requires this USB to RCA adapter)
Speaker Impedance: 8 ohms to 2 ohms
Voltage input range: 90 to 264 VAC, 127 to 370 VDC
Features & specs
General
Number of Channels--- Power Output per Channel (8 ohms)20
Power Output per Channel (6 ohms)--- Power Output per Channel (4 ohms)---
Frequency Bandwidth--- THD--- Minimum Impedance--- Bridged Power per Channel--- Speaker Outputs--- THX Certification--- Width (inches)14-7/8
Height (inches)3
Depth (inches)10-1/4
Weight6 pounds
Parts Warranty1 Year
Labor Warranty1 Year
Inputs & Outputs
Number of Inputs--- Input Type--- Removable Power Cord--- Level Controls---
Speaker ConnectorsY