



2-Channel 400W Bridgeable Power Amplifier

SC2-100

SKU: 66913

The SC2-100 is a 2-channel amplifier providing 100W per channel (400W when bridged for higher output applications) and independent level control, making installation easier and more straight forward than ever before.

Offering the classic SpeakerCraft power and stability that you™ve come to know and trust, the New SC2-100 brings extremely high current power to a custom installed A/V System in a remarkably convenient way. Featuring audio circuitry constructed using the fi nest materials available, including 1% metal film resistors, high quality capacitors and oversized heat sinks that ensure proper cooling without the need for a noisy fan. This 2-channel amplifier provides 100W per channel (400W when bridged for higher output applications) and independent level control, making installation easier and more straightforward than ever before.}

Features

- Delivers real world power of 100W per channel at 8? and 200W per channel at 4?.
- Features three turn-on modes: Music Sense, External Voltage Trigger and Manual Turn-On via the front panel switch
- Can be operated in a bridged mono configuration, delivering 400W.
- Features independent level control, enabling precise volume matching to the rest of the system.
- Oversized heat sinks inside the System Integration Amplifiers allow the amplifier circuitry to stay cool even when operating.
- Increased isolation between channels eliminates cross talk.
- Dimensions (W x H) 17.25 x 2.25 in

Specifications 100 watts RMS per channel into 8 Ohms (all channels driven) 220 watts RMS per channel into 4 Ohms (all channels driven) Channels are bridgeable to 400 watts RMS into 8 Ohms Total Harmonic Distortion: 0.2% THD from 20Hz to 20kHz 12-volt control out Removable line cord Two year limited warranty Rack mount ears included Tested and certified to US, Canada, EU, and Australian safety and EMC standards Overall dimensions: 17 1/4" (43.81 cm) wide x 2 1/4" (5.6 cm) high (including feet) General Number of Channels2 Watts RMS Per Channel100 Shipping Info Length 23 (Inches) Width 16.7 (Inches) Height 5.7 (Inches) Weight 13.45 (Lbs) Unit of Measure Each UPC664254999666 Master Pack Qty2 Other Specifications 100 watts RMS per channel into 8 Ohms (all channels driven) 220 watts RMS per channel into 4 Ohms (all channels driven) Channels are bridgeable to 400 watts RMS into 8 Ohms Total Harmonic Distortion: 0.2% THD from 20Hz to 20kHz 12-volt control out Removable line cord Two-year limited warranty Rack mount ears included Tested and certified to US, Canada, EU, and Australian safety and EMC standards Overall dimensions:17 1/4" (43.81 cm) wide x 2 1/4" (5.6 cm) high (including feet)